
#### **Elementary Statics**

#### **Vector Components and Vector Addition in Two Dimensions**

## **Cartesian Components of Vectors in Two Dimensions**

- Given the *magnitude* of a vector and the *direction* of the vector relative to a set of *reference axes*, the vector can be expressed in terms of its *components* along those axes.
- For our convenience, it is usually beneficial to have the reference axes be mutually perpendicular.
- o In the diagram,  $V_x$  and  $V_y$  represent the components of the vector  $V_y$  along the mutually perpendicular X and Y axes.



- The parallelogram formed by  $V_x$  and  $V_y$  is now a *rectangle*, and the triangle formed by  $V_x$  and  $V_y$  is now a *right triangle*.
- $\circ$  So, if the magnitude of the vector V is |V| = V, we now have

$$\boxed{V = V_x + V_y = V \cos(\theta) \, \underline{i} + V \sin(\theta) \, \underline{j}}$$


# Example #1:

Given: A force F has magnitude |F| = F = 100 (lbs) and angle  $\theta = 30$  (deg).

Find: Express the force  $\underline{F}$  in terms of the unit vectors  $\underline{i}$  and  $\underline{j}$ .

#### Solution:

$$F = 100\cos(30) \, \underline{i} + 100\sin(30) \, \underline{j} \approx 86.6 \, \underline{i} + 50 \, \underline{j} \, \text{(lb)}$$




## Example #2:

Given: A force F has magnitude |F| = 100 (lbs) and angle  $\theta = 120$  (deg).

Find: Express the force  $\underline{F}$  in terms of the unit vectors  $\underline{i}$  and  $\underline{j}$ .


Solution:



### Example #3:

Given: **Force**  $\vec{F} = 70 \, i + 50 \, j$  (lb).

Find: Magnitude and direction of F.



Solution:


$$|F| = \sqrt{70^2 + 50^2} \approx 86.0 \text{ (lbs)}$$
 and  $\theta = \tan^{-1}(50/70) \approx 10^{-1}$ 

$$\theta = \tan^{-1}(50/70) \approx \begin{cases} 35.54 \text{ (deg)} \\ 0.6202 \text{ (rad)} \end{cases}$$

# Example #4:

Given: **Force**  $\vec{E} = -50 \, \hat{i} + 70 \, j$  (lb).

Find: *Magnitude* and *direction* of  $\underline{F}$ .



Solution:

$$|F| = \sqrt{(-50)^2 + 70^2} = 86.0 \text{ (lb)}$$
 
$$\theta = \tan^{-1}(70 / -50) = \begin{cases} -54.46 + 180 = 125.5 \text{ (deg)} \\ -0.9505 + \pi = 2.191 \text{ (rad)} \end{cases}$$

Notice that care must be taken to identify the correct quadrant when using the inverse tangent function. In this case, 180 degrees (or  $\pi$  radians) was added to the calculator result to find the correct result in the second quadrant.

## **Vector Addition using Cartesian Components in Two Dimensions**


To *add two* or *more vectors*, simply express them in terms of the same unit vectors, and then add *like components*.

# Example #5:

Given: Forces

$$|F_1| = 150 \text{ (lb)}, \ \theta_1 = 20 \text{ (deg)}$$

$$|F_2| = 100 \text{ (lb)}, \ \theta_2 = 60 \text{ (deg)}$$



Find: a) **Resultant force** F acting on the support in terms of the unit vectors shown.

b) *Magnitude* and *direction* of F.

#### Solution:

a) The total force is the vector sum of the two forces.


$$E_1 = 150\cos(20) \, \underline{i} + 150\sin(20) \, j \approx 140.95 \, \underline{i} + 51.3 \, j \, \text{(lb)}$$

$$E_2 = -100\cos(60) \, \underline{i} + 100\sin(60) \, \underline{j} \approx -50 \, \underline{i} + 86.6 \, \underline{j} \, \text{(lb)}$$

$$\vec{F} = \vec{F}_1 + \vec{F}_2 \approx (140.95 - 50) \, \vec{i} + (51.3 + 86.6) \, \vec{j} = 90.95 \, \vec{i} + 137.9 \, \vec{j} \text{ (lb)}$$

b) 
$$|E| \approx \sqrt{90.95^2 + 137.9^2} \approx 165.2 \approx 165 \text{ (lb)}$$


$$\theta \approx \tan^{-1}(137.9/90.95) \approx \begin{cases} 56.6 \text{ (deg)} \\ 0.988 \text{ (rad)} \end{cases}$$



### Example #6: (3 forces)

Given:  $|F_1| = 50$  (lb);  $|F_2| = 75$  (lb),  $|F_3| = 150$  (lb)

- all directions are as shown in the diagram



Find: a) *Resultant force*  $\mathcal{F}_R$  acting on the support in terms of the unit vectors shown.

b) *Magnitude* and *direction* of  $\mathcal{E}_R$ .

Solution:

a) 
$$E_1 = 50\left(\frac{4}{5}i + \frac{3}{5}j\right) = 40i + 30j$$
 (lb)  
 $E_2 = 75\left(\sin(30)i + \cos(30)j\right) \approx 37.5i + 64.9519j$  (lb)  
 $E_3 = 150\left(-\cos(30)i + \sin(30)j\right) \approx -129.9i + 75j$  (lb)  
 $E_R \approx \left(40 + 37.5 - 129.9\right)i + \left(30 + 64.95 + 75\right)j$   
 $\approx -52.4038i + 169.952j$   

$$\Rightarrow \boxed{E_R \approx -52.4i + 170j}$$

b) 
$$|F_R| \approx \sqrt{(-52.4038)^2 + (169.952)^2} \approx 177.848 \approx 178 \text{ (lb)}$$

$$\theta \approx \tan^{-1} \left(\frac{169.952}{-52.4038}\right) \approx -72.86 + 180 \approx 107 \text{ (deg)}$$

